

## DESCRIPTION

The Vista EX control surface provides large amounts of physical control within a compact footprint, capable of delivering small to large scale shows.

Featuring 12 customisable playback faders and 60 assignable buttons, Vista EX ensures that you have enough hands-on control for even the most demanding of shows, whilst providing the flexibility to adapt to any genre of production or event. Vista EX also features 4 function keys, which, when combined with the 60 playback buttons offers up to an incredible 300, user definable, actions per page, providing unrivalled control from a unit that is so small.

## FEATURES

- 12 (assignable) playback faders
- 60 (assignable) playback buttons
- 2 physical DMX outputs
- Grand master intensity fader
- Dedicated master cue list playback controls
- 12 user keys
- 4 function keys
- 8 encoders
- Unlimited pages
- RGB back-lit playback buttons
- Sturdy construction

## ORDERING INFORMATION

CQ676-1010: Vista EX control surface no channels

## RELATED PRODUCTS

Q678-1128: Vista 128 channel dongle  
Q678-1256: Vista 256 channel dongle  
Q678-1512: Vista 512 channel dongle  
Q678-1024: Vista 1024 channel dongle  
Q678-2048: Vista 2048 channel dongle  
Q678-4096: Vista 4096 channel dongle  
Q678-8192: Vista 8192 channel dongle

## OVERALL SPECIFICATIONS

Net Dimensions:	Width: 526mm / 21" Height: 75mm / 3" Depth: 346mm / 14"
Net Weight:	6 kg / 13 lbs
Shipping Dimensions:	Width: 550mm / 22" Height: 130mm / 5" Depth: 420mm / 17"
Shipping Weight:	7 kg/ 15 lbs
Power Supply:	12 VDC External PSU
Power Input Rating:	12V DC +/- 10%
Power Consumption:	1500 mA
Power Connectors In:	XLR 4-pin
DMX Data Connectors In/Out:	Neutrik XLR 5-pin
USB Connectors In:	USB (Type B)
DMX Outputs:	2
Desk Light Socket:	Neutrik XLR 3-pin
Cooling System:	Convection Cooled
Operating Temperature:	0°C to 40°C (0 to 104 °F)
Construction:	Powder Coated Steel
Colour:	Grey Surface / Red Frame
Backlit Key Panel:	RGB
Internal Dongle:	USB (Type A)
IP Rating:	IP20
Assignable Playback Faders:	12
Assignable Playback Buttons:	60
Grand Master:	1
User Keys:	12
Power Light Indicator:	1
Function Keys:	4

## DIMENSIONS

